

# PLC-XC10

Brilliant Ideas for Your Business.

# SANYO

- Brightness: 3,000 ANSI lumens
- XGA Resolution
- Network integration and WLAN solutions (optional)
- Automatic horizontal and vertical trapezoid adjustment
- DVI Input, Monitor Output
- 3-years guarantee



# PLC-XC10

Brilliant Ideas for Your Business.

# SANYO

## TECHNICAL DETAILS

## PLC-XC10

Category	Business & Education
Panel	3 x 1.0" TFT p-Si (Microlens)
Lamp	300 W NSH
Brightness ANSI lumens	3,000
Lamp Service Life	1,500 Hours
Standard Lens	F = 1.7 – 2.1 / f = 33.6 – 43.2 mm
Aspect Ratio	1.65 – 2.1 : 1
Distance	1.3 – 10.1 m (please use the three-dimensional distance calculator at <a href="http://www.sanyo.de">www.sanyo.de</a> )
Contrast Ratio	450 : 1
Resolution in pixels	1,024 x 768 (XGA)
Horizontal Resolution	750 TV lines
Uniformity	85 %
Bandwith / Frequency	140 MHz, horizontal 15 ~ 100 kHz, vertical 50 ~ 100 Hz
Color Systems	PAL, SECAM, NTSC, NTSC4.43, PAL-M/N
Connections	Input 1: DVI-I (digital/HDCP/analog); Audio: 3.5 mm Stereo Jack Input 2: D-Sub15 (RGB/SCART-RGB) or monitor output; Audio: 3.5 mm Stereo Jack Input 3: 3x Cinch (Video/Y-Pb/Cb-Pr/Cr); Audio: 2x Cinch (R/L-mono) Input 4: Mini-DIN 4-pin (S-Video); Audio: shared with Input 3 Audio Output: 3.5 mm Stereo Jack (variabel) Control Input 1: Mini-DIN 8-pin (RS232) Control Input 2: USB Typ B (mouse control) Others: USB Typ A (USB-key)
Audio	1 W Mono
Keystone Correction	vertical +/- 40°, horizontal +/- 20°
Lens-Shift	Fix U/D Ratio 9 : 1
HDTV Signals	720p / 1,035i / 1,080i (HDTV-compatible)
Computer Compatibility	S-XGA / XGA / S-VGA / VGA / Mac
Zoom / Focus	1.3x / motorized
Power Consumption	400 W / 100 – 240 V
Warranty	3 Years Warranty
Dimensions (W x H x D) in mm	390 x 112 x 274
Weight	5.8 kg
Standard Accessories	IR remote control with laser pointer, batteries, operating manual, DVI/D-Sub15-cable, USB-cable, lens cover with fastener and cord, power cable, dust cover
Optional Accessories	Multi Card Imager (with W-LAN-Card or CompactFlash-Card or LAN-Card), SCART/D-Sub15-cable, USB Security Key, USB Security Master Key

For more information about optional accessories, please see the "Network Solutions and Accessories" brochure.



Technical specifications are subject to change without notice. Status 02/2005

